



OVERVIEW

- ♦ General-purpose fluorescent industrial style luminaire featuring a wide symmetrical reflector, which shields and controls the output of the lamps
- ♦ Available with 2 lamps

CONSTRUCTION

- ♦ Housing—Die formed from code gauge cold rolled steel. End plates quickly convert to snap-in continuous row joiners for uninterrupted wireway. Easy install socket plates have snap-in action. Reflectors attach with quarter-turn fasteners for easy installations and maintenance. Two reflectors with provided aligners are used on all 6Ft. and 8Ft. fixtures. Sufficient knockouts are provided on the back and ends for all electrical connection. Baked white enamel finish provides a minimum reflectivity of 87%. Optional 20GA housing is available
- ♦ Sockets—1/4 twist bi-pin or optional rotary locking type.

PROJECT _____

TYPE _____

QTY. _____

APPLICATIONS

- ♦ Industrial
- ♦ Commercial
- ♦ General Lighting Areas

INSTALLATION

- ♦ Designed for surface, stem or chain hanging, mounted individually or in continuous row.

ELECTRICAL

- ♦ All electrical components are UL or ETL Listed. Lamp holders provided ensure positive lamp retention.
- ♦ Sufficient knock-outs are provided for connections and through wiring.
- ♦ Electronic class P, thermally protected ballasts standard.
- ♦ Green ground screw installed in channel.
- ♦ All fixtures come equipped with ballast disconnect to meet NEC code 410.73.

APPROVALS

- ♦ ETL Listed. Suitable for dry and damp locations with ETL Damp Label.



ORDERING GUIDE

Fill in the boxes below with the corresponding **bold** options.

Example: **IND201-4-2-32-T8-B8IN-MV-AR**

IND201		2				MV	AR				
SERIES	FIXTURE LENGTH	NO. OF LAMPS	WATTAGE	LAMP TYPE	BALLAST TYPE	VOLTAGE	REFLECTOR	OPTIONS			
IND201	T8						AR	Aluminum Reflector	EM1	Emergency Battery Back Up 1 Lamp Operation	
	4 4FT.	2	32	T8	B8IN	MV			EM2	Emergency Battery Back Up 2 Lamp Operation	
	8 8FT.	2	32-TAN	T8	B8IN	MV			2C	2 Circuit	
	8 8FT.	2	59	T8	B8SI	MV	DIM Dimming—Consult Factory				
	T5 / T5HO						Accessories				
	4 4FT.	2	28	T5	B5P	MV	VH	V-Hanger			
	8 8FT.	2	28-TAN	T5	B5P	MV	CH	Chain			
	4 4FT.	2	54	T5HO	B5HOP	MV	SS	Stem Set			
	8 8FT.	2	54-TAN	T5HO	B5HOP	MV	CS	Cable Set			
	T12										
	8 8FT.	2	60 75	T12	B2SI	MV					

Consult Factory for additional configurations and options not listed or shown.

Note:

TAN—Tandem Units, double the number of lamps

For T5/T5HO Fixtures—

T8/T5 Conversion Sockets are used to meet fixture length

Ballast

B8IN T8, Instant Start NBF (Standard)

B8SI T8, Instant Start, Slimline

B5P T5, Program Start

B5HOP T5 HO, Program Start


B2SI T12, Instant Start, Slimline

Voltage

MV 120-277V

DIMENSIONS

END VIEW



END VIEWS

